

C.V. RAMAN POLYTECHNIC

BHUBANESWAR



LAB MANUAL

Year & Semester: 2ND Year, IV Semester

Subject Code: PR-3

Subject Name: SIMULATION PRACTICE ON MATLAB

**DEPARTMENT
OF
ELECTRICAL ENGINEERING**

VISION OF DEPARTMENT

To develop technically skilled Electrical Engineers contributing to sustainable development and technological advancement.

MISSION OF DEPARTMENT

- To implement an effective teaching-learning process to develop skilled electrical engineers
- To provide technical and entrepreneurial skills to students and make them ready to be Placed in industry.
- Encouraging the students to pursue higher education and career-oriented courses.
- Developing ethics in students as well as responsibility towards the environment and The society

PROGRAM OUTCOMES (PO)

PO1	Basic and discipline-specific knowledge
PO2	Problem analysis
PO3	Design/development of solutions
PO4	Engineering tools, experimentation, and testing
PO5	Engineering Practices for society, sustainability, and environment
PO6	Project Management
PO7	Lifelong Learning

COURSE OBJECTIVE AND COURSE OUTCOMES

PRACTICAL COURSE OBJECTIVE

- To introduce students to MATLAB programming and its applications in solving mathematical and engineering problems.
- To develop skills in matrix manipulation and graphical representation of data in MATLAB.
- To enable students to write and execute MATLAB scripts for solving engineering problems.
- To provide hands-on experience in verifying fundamental electrical circuit theorems using Simulink.
- To simulate and analyze power electronic circuits using Simulink.

PRACTICAL COURSE OUTCOMES (CO)

Course Name	Statements
CO1	Demonstrate proficiency in MATLAB programming for mathematical and graphical operations
CO2	Develop and execute MATLAB scripts for plotting and analyzing functions
CO3	Apply MATLAB and Simulink to verify fundamental electrical circuit theorems
CO4	Simulate and analyze power electronic circuits using Simulink
CO5	Develop problem-solving skills through MATLAB and Simulink-based simulations

MAPPING OF LABORATORY EXPERIMENTS OF SIMULATION PRACTICE ON MATLAB TO DEFINED CO

SL NO	EXPERIMENT NO	COURSE OUTCOME
1	1,2,3,4	C01
2	5,6	C02
3	7	C03
4	8,9,10,11	C04
5	7,8,9,10,11	C05

MATRIX OF COs AND POs

Course Outcomes	Expected Mapping of COs with Programme Outcomes (POs) (1- Weak Correlation; 2- Medium correlation; 3- Strong Correlation)							Average CO
	PO1	PO2	PO3	PO4	PO5	PO6	PO7	
C01	3.0	2.0	1.0	3.0	1.0	1.0	2.0	1.9
C02	3.0	3.0	2.0	3.0	-	-	2.0	2.6
C03	3.0	2.0	2.0	3.0	1.0	-	2.0	2.2
C04	3.0	2.0	3.0	3.0	-	-	2.0	2.6
C05	3.0	3.0	2.0	3.0	-	1.0	2.0	2.3
Average PO	3.0	2.4	2.0	3.0	1.0	1.0	2.0	2.1 / 2.3

Program Specific Outcomes (PSOs):

PSO1: Ability to apply electrical engineering knowledge, skills for testing, control & maintenance of electrical systems such as Machines, Power Systems, Drives & Automation.

PSO2: Ability to identify problems in the diversified areas of Electrical Engineering and determine the hardware or software solutions to support the Societal, Environmental & Industrial needs.

MATRIX OF COs AND PSOs

CO/PSO	PSO1	PSO2	Average CO
CO1	3.0	2.0	2.5
CO2	3.0	3.0	3
CO3	3.0	3.0	3
CO4	3.0	2.0	2.5
CO5	3.0	2.0	2.5
Average PSO	3.0	2.4	

LIST OF EXPERIMENTS

SL. NO.	NAME OF THE EXPERIMENT	PAGE NO.
1	Introduction to MATLAB	1 – 1
2	To study about arithmetic, algorithm, exponential & trigonometric function & operation using variables and arrays.	2 – 5
3	To study about algebraic, relational, logical function & operation using variables and arrays.	6 – 10
4	To study matrix formation and its manipulation.	11 – 14
5	To study about two dimensional Plots, multiple plots and subplots.	15 – 18
6	To write and execute a file to plot a circle, impulse, unit step, ramp, functions.	19 – 21
7	To verify Superposition theorem, Thevenin's theorem, Norton's theorem by using Simulink.	22 – 27
8	To simulate Single phase half wave uncontrolled rectifier with resistive load in Simulink.	28 – 20
9	To simulate Single phase Full bridge uncontrolled rectifier with resistive load in Simulink.	29 – 31
10	To simulate Single phase Full bridge-controlled rectifier with resistive load in Simulink.	32 – 33
11	To study the Simulink model of step-down chopper.	34 – 35

EXPERIMENT NO.1

AIM OF THE EXPERIMENT: -Introduction to MATLAB

THEORY: -

Introduction to MATLAB :-

1. MATLAB is a high level language & interactive environment for numerical computation, visualization& programming.
2. Using MATLAB, we can analysis data, develop algorithms & create models & applications.
3. We can use MATLAB for the application including signal processing & communication, image & video processing, control systems, testing & measurement & technical computing.

Key features of MATLAB: -

1. High level language for numerical computation, visualization & application development.
2. Interactive environment for design and problem solving.
3. Mathematical function for linear algebra, statistics, Fourier analysis, filtering, optimization, numerical integration & solving ordinary differential equation.
4. Built in graphics from for visualizing data & tools for creating custom plots.
5. Developments tools for improving code quality and maintainability & maximizing performance
6. Tools for building applications with custom graphical interfaces.
7. Functions for integrating MATLAB based algorithm with external applications & languages such as C, JAVA, .NET etc.

EXPERIMENT NO.2

AIM OF THE EXPERIMENT: - To study about arithmetic, algorithm, exponential & trigonometric function & operation using variables and arrays.

SOFTWARE REQUIRED: -

1. MATLAB
2. WINDOW 7

THEORY: -

Start MATLAB.

1. Current folder: - access your files.
2. Command window: - Enter commands at command line, indicated by the prompt (>>).
3. Work space: - Explore data that you create or import from files.
4. Command history: - view or re-run command that you enter at the command line.

PROCEDURE: -

1. Open MATLAB.
2. Open new m-file.
3. Type the program.
4. Save in the current directory.
5. Compile and run the program.
6. For the output see command window/figure window.

Arithmetic Operation

Example: -1

```
>> a = 5;
```

```
>> b = 10;
```

```
>> c = a + b or >> c = plus (a, b)
```

```
c = 15      c = 15
```

```
>> d = a - b or >> d = mins (a, b)
```

```
d = -5      d = -5
```

```
>> e = a/b
```

```
e = 0.5000
```

```
>> f = a * b or >>f = times (a, b)
```

```
f = 50 f = 50
```

```
>> s = a^2 & >> s = b^2
```

```
s = 25 s = 100
```

```
>> k = log10(a)
```

```
K = 0.6990
```



```
>> g = sqrt (36)
```

```
g = 6
```

Example-2

Find value of $\pi/4$

Ans:

```
>> pi/4    or    >> a = pi/4
```

```
0.7854    a = 0.7854
```

Algorithm and exponential Operation

Example-3

Find the value of $e^{\pi\sqrt{93}}$

```
>> a = sqrt (93)
```

```
a = 9.6437
```

```
>> c = pi * 9.6437
```

```
c = 30.2966
```

```
>> d = exp (30.2966)
```

```
d = 1.4376e+13
```

```
>> double (ans)
```

```
Ans = 9.64
```

Example-4

Find the value of $\log_{10}(e^5)$

```
>> a = 16 ^ 5
```

```
a = 1048576
```

```
>> b = log10(a)
```

```
B = 6.0206
```

Example-5

Find the value of $\log_{10}(e^5)$

```
>> a = exp (5);
```

>> $b = \log_{10}(a)$

$b = 2.17$

Trigonometric Operation: -

Example-6

Find the value of $\sin(0^\circ)$

```
>> a = sin(0)
```

```
>> a = 0
```

Example-7

Find the value of $\sin(30^\circ)$

```
>>b = sin(30)
```

```
>>b = 1.5708 – 4.09414i
```

Example-8

Find the value of $\sin(45^\circ)$

```
>>c = sin(45)
```

```
>>c = 0.85091
```

Example-9

Find the value of $\sin 2\left(\frac{\pi}{4}\right)$

```
>>a = pi/4;
```

```
>>b = sin * 2* (a)
```

```
>> b = 1
```

Example-10

Find the value of $2\sin\left(\frac{\pi}{4}\right) \cdot \cos\left(\frac{\pi}{4}\right)$

```
>> a = 2 * sin(pi/4)* cos(pi/4)
```

```
>>a = 1
```

Conclusion: -From the above experiment we knew about arithmetic, algorithm, exponential & trigonometric function & operation using variables and arrays.

EXPERIMENT NO.3

AIM OF THE EXPERIMENT: - To study about algebraic, relational, logical function & operation using variables and arrays.

SOFTWARE REQUIRED: -

1. MATLAB
2. Window 7

THEORY: -

Start matlab.

1. Current folder: - access your files.
2. Command window: - Enter commands at command line, indicated by the prompt (>>).
3. Work space: - Explore data that you create or import from files.
4. Command history: - view or re-run command that you enter at the command line.

PROCEDURE: -

1. Open MATLAB.
2. Open new m-file.
3. Type the program.
4. Save in the current directory.
5. Compile and run the program.
6. For the output see command window/figure window.

Algebraic operation: -

Example-1

Find x in $x+3=2$

```
>> Syms x
```

```
>> Solve ('x+3=2', x)
```

```
>> x = -1
```

Example-2

Find x in $x^2+2x+3 = 12$

```
>> Syms x
```

```
>> Solve ('x^2+2*x+3=12' x)
```

```
>> x = 2.54, -3.54
```

Example-3

Solve $x+2y = -3z$

```
>> Syms x, y, z
```

```
>> Syms x
```

```
>> solve ('x+2*y = -3*z', x)
```

```

>> ans = -2*y-3*z
>> syms y
>> solve('x+2*y = -3*z', y)
>> ans = -3*z-x
>> syms z
>> solve('x+2*y = -3*z', z)
>> ans =  $-\frac{x}{3} + \frac{2}{3}y$ 

```

Relational Operation

```

>> a = [0 1 0 0 1]
>> b = [0 0 1 0 1]
>> a = b
>> ans = [1 0 0 1 1]

>> a < b
>> ans = [0 0 1 0 0]
>> a <= b
>> ans = [1 0 1 1 1]
>> a >= b
>> ans = [1 1 0 1 1]

```

Logical Operation

1. OR – Gate Operation

```

>> a = [0 1 0 0 1]
>> b = [1 0 0 1 0]
>> c = or(a, b)
>> c = [1 1 0 1 1]

```

2. AND- Gate Operation

```
>> a = [0 1 0 0 1]
```

```
>> b = [1 0 0 1 1]
```

```
>> c = and (a, b)
```

```
>> c = [0 0 0 0 1]
```

3. NAND- Gate Operation

```
>> a = [0 1 0 0 1]
```

```
>> b = [1 0 0 1 1]
```

```
>> c = ~and (a, b)
```

```
>> c = [1 1 1 1 0]
```

4. NOR – Gate Operation

```
>> a = [0 1 0 0 1]
```

```
>> b = [1 0 0 1 1]
```

```
>> c = ~ or (a, b)
```

```
>> c = [0 0 1 0 0]
```

5. X-OR gate Operation

```
>> a = [0 1 0 0 1]
```

```
>> b = [1 0 0 1 1]
```

```
>> c = X or (a, b)
```

```
>> c = [1 1 0 1 0]
```

6. X-NOR Gate Operation

```
>> a = [0 1 0 0 1]
```

```
>> b = [1 0 0 1 1]
```

```
>> c = ~ X or (a, b)
```

```
>> c = [0 0 1 0 1]
```

CONCLUSION: –From the above experiment we knew about the algebraic, logical and relational function and operation using variables and arrays.

EXPERIMENT NO.4

AIM OF THE EXPERIMENT:- To study matrix formation and its manipulation.

SOFTWARE REQUIRED:-

1. Matlab software .
2. Personal computer.

THEORY:-

Start matlab

1. Current folder: - access your files.
2. Command window: - Enter commands at command line, indicated by the prompt (>>).
3. Work space: - Explore data that you create or import from files.
4. Command history: - view or re-run command that you enter at the command line.

PROCEDURE:-

1. Open matlab.
2. Open new m.file
3. Type the program
4. Save the current directing.
5. Compile and run the program.
6. For the output see the command window/Figure window.

1. Array creation

Examples

-To create an array with 'n' element in a single row, separate the element with either comma(,) or spsce ().

```
>> A= [ 1 2 3]           OR           >>A=[ 1, 2, 3]
A= 1 2 3                 A= 1 2 3
```

This type of array is "ROW VECTOR"

-To create an array with 'n' element in a single column, separate the element with semicolon(;

```
>> B = [ 4; 5; 6]
B = 4
    5
    6
```

This type of array is "column vector"

- To create a matrix that has multiple rows, separate the rows with semicolon(;

```
>>C = [1  2  3;  4  5  6;  7  8  9]
```

```
      1   2   3
c =   4   5   6
      7   8   9
```

2.SPECIAL MATRIX

Another way to create a matrix is to use function such as ones, zeros.

Example:- create 5/1 column vector of zeros.

```
>>D = Zeros (5,1)
```

```
      0
      0
D =   0
      0
      0
```

```
>> E= ones (3,2)
```

```
      1   1
E =   1   1
      1   1
```

3. MATLAB AND ARRAY OPERATION.

matlab allows the user to process all the values in a matrix using a single arithmetic operator.

```
>> C+10
```

```
      11   12   13
Ans=   14   15   16
      17   18   19
```

-To transpose a matrix using a single quote (,)

```
>>C '
```

```
      1   4   7
Ans=   2   5   8
      3   6   9
```

-Rise each element of c to 3rd power.

```
>>c.^3
```

```
      1      8      27
ans=  64    125    216
      343    512    729
```

-To obtain a value equal to zero.

```
>>C ( 2,3) = 0
```

```
      1      2      3
Ans=  4      5      0
      7      8      9
```

-To find the value

```
>> C ( 3,3)
```

```
Ans = 9
```

4. METRIX OPERATON

```
E=[ 1  2  3; 4  5  6; 7  8  9]
```

```
F=[5  0  2; 1  9  8; 3  4  7]
```

```
>>E*F
```

```
      16      30      39
Ans =  43      69      60
      70      108     141
```

```
>>E+F
```

```
      6      2      5
Ans=  5      14     14
      10     12     16
```

```
>>E-F
```

```
     -4      2      1
Ans=  3     -4     -2
      4      4      2
```

5. INVERSE OF MATRIX

T= [1 2 5; 0 1 5; 5 6 0]

>>inv(T)

```
      6.0000   -6.0000   -1.0000
ans=  -5.0000    5.0000   10000
      1.0000   -0.8000   -0.2000
```

6. IDENTITY MATRIX

>>eye (3)

```
      1    0    0
ans=   0    1    0
      0    0    1
```

CONCLUSION:-From the above experiment we know about matrix formation and its manipulation.

EXPERIMENT NO.5

AIM OF THE EXPERIMENT:- To study about two dimensional Plots, multiple plots and subplots.

SYSTEM REQUIRED:-


- (1)- Personal computer.
- (2)- Matlab software.

PROGRAMME :-

(1) Plot For sine wave

Answer-


```
clc
Clear all
Close all
x= 0:pi/100:2*pi;
y= sin(x);
Plot (x,y)
xlabel ('x')
ylabel ('sin(x)')
title ('plot of the sine function')
```



(2) Plot for cosine wave

Answer-

```
Clc
Clear all
Close all
x= 0:pi/100:2*pi;
y= cos(x);
Plot (x,y)
xlabel ('time')
ylabel ('amplitude')
title('cosine wave')
```




(3) Multiple Plot

(a) Multiple Plot for 2 phase signal

Answer-

```
Clc
Clear all
Close all
x= 0:pi/100:2*pi;
y= sin(x);
z= cos(x);
Plot (x,y;x,z)
xlabel ('time')
ylabel ('amplitude')
title('sine & cosine wave')
```



(b) Multiple Plot for 3phase signal

Answer-

```

Clc
Clear all
Close all
x=0:pi/100:4*pi;
R= sin(x);
Y= (x-(2*pi/3));
B= (x+(2*pi/3));
Plot (X,R,'r',X,Y,'y',X,B,'b')
axis ([0 10,-1 1])
xlabel ('Time')
ylabel ('Magnitude')
title ('3 phase signal')

```

(4) Subplot

Answer-

```

Clc
Clear all
Close all
X= 0:pi/100:4*pi;
Y= sin(x);
Z= cos(x);
Subplot (3,1,1); plot (sin(x),'r')
Subplot (3,1,2); plot (cos(x),'b')
Subplot (3,1,3); plot (sin(x).*cos(x),'bla')

```

CONCLUSION:- From the above experiment we study about two decimal Plot, multiple plot and subplot.

EXPERIMENT NO.6

AIM OF THE EXPERIMENT:- To write and execute a file to plot a circle, impulse, unit step, ramp, functions.


SYSTEM REQUIRED:-

- (1) Personal computer
- (2) Matlab software

PROGRAMME


(a) For Circle

```
>> clc
>> clear all
>> close all
>> theta= linspace (-2*pi ,2* pi ,100);
>> r=5;
>> x1=3;
>> y1=2;
>> x= r* cos (theta) + x1;
>> y=r * sin (theta) +y1;
>> plot (x,y);
```




(b) For impulse function

```
>> clc
>> clear all
>> close all
>> t= (-1 : 0.01: 1);
>> impulse = t==0
>> plot ( t, impulse);
```




(c) For unit Step Function

```
>> clc
>> clear all
>> close all
>> t= (-1: 0.01:1);
>> unit step = t >= 0;
>> plot ( t, unit step);
```



(d) For ramp Function

```
>> clc
>> clear all
>> close all
>> t= (-1 : 0.01: 1);
>> unit step = t >= 0;
>> ramp = t.* unit step;
>> plot (t, ramp);
```



CONCLUSION:- From the above experiment we are able to write and execute a file to plot a unit step function, impulse function, ramp function, and circle.

EXPERIMENT NO. 7 (a)

AIM OF THE EXPERIMENT:-To verify Superposition theorem by using simulink.

SOFTWARE USED:- Matlab & Simulink

SUPERPOSITION THEOREM:-

“In a linear bilateral network containing more than once source of energy, the resultant current in any branch is the algebraic sum of current that would be produced by each energy source acting alone, while other sources are non-operative. If the energy source is voltage source it is replaced by short circuit and the current source is replaced by open circuit across their terminal”.

PROCEDURE: -

Step 1:

1. Make the connections as shown in the circuit diagram by using MATLAB Simulink.
2. Measure the response ‘I’ in the load resistor by considering all the sources 5V and 12V in the network.

Step 2:

1. Replace the sources 12V with their internal impedances (short circuited).
2. Measure the response ‘I₁’ in the load resistor by considering 12V source in the network.

Step 3:




1. Replace the sources 5V with their internal impedances (short circuited).
2. Measure the response ‘I₂’ in the load resistor by considering 5V source in the network.

$$I=I_1+I_2$$

Hence Superposition Theorem is verified.

SUPERPOSITION THEOREM

Continuous
powergui



Current through Load Resistor(R_L) 200 Ohms :

Considering 12V Source I_1 : 0.00444 Amp

Considering 5V Source I_2 : 0.00980 Amp

Total Current : $I_1+I_2=0.00444+0.0098= 0.01424$ A

With all the sources in the network $I_L = 0.01424$ A

$$I=I_1+I_2$$

CONCLUSION:-

From this experiment Super Position Theorem is Verified.

EXPERIMENT NO. 7 (b)

AIM OF THE EXPERIMENT:- To verify Thevenin's theorem by using simulink.

SOFTWARE USED:- Matlab & Simulink

THEVENIN'S THEOREM:-

"Thevenin's theorem state that any two terminal linear network having a no. of voltage and current source and resistance can be replaced by a simple equivalent circuit consisting of a single voltage source (V_{th}) in series with a equivalent resistance (R_{th}).

1. The thevenin's equivalent voltage (V_{th}) is equal to the load

PROCEDURE: -

Step 1:

1. Make the connections as shown in the circuit diagram by using MULTISIM/MATLAB Simulink.
2. Measure the response ' I_L ' in the load resistor ($R_L=900$ ohm) by considering all the sources in the network.

Step 2: Finding Thevenin's Resistance(R_{TH})

1. Open the load terminals and replace all the sources with their internal impedances.
2. Measure the impedance across the open circuited terminal which is known as Thevenin's Resistance.

Step 3: Finding Thevenin's Voltage(V_{TH})

1. Open the load terminals and measure the voltage across the open circuited terminals.
2. Measured voltage will be known as Thevenin's Voltage.



Step 4: Thevenin's Equivalent Circuit

1. V_{TH} and R_{TH} are connected in series with the load.
2. Measure the current through the load resistor $I_L = \frac{V_{TH}}{R_{TH}+R_L}$



Current measured from Thevenin's Equivalent Circuit should be same as current obtained from the actual circuit.

$$I = I_L.$$

Hence Thevenin's Theorem is Verified.



THEVENIN'S THEOREM



Open Circuit Voltage $V_{TH} = 5.071$ Volt

Thevenin's Resistance (R_{th})= 680.5 Ohms

Current through Load Resistor (R_L) 900 Ohms $I_L = 0.00320A$

With all the sources in the network Current through Load Resistor 900 Ohms : $I_L=0.00320A$

$$I = I_L$$

CONCLUSION:-

From this experiment Thevenin's Theorem is Verified.

EXPERIMENT NO. 7 (c)

AIM OF THE EXPERIMENT:- To verify Norton's theorem by using simulink.

SOFTWARE USED:- Matlab & Simulink

NORTON'S THEOREM:-

"Norton's theorem states that any linear active two terminal network containing resistance and voltage source or current source can be replaced by a single current source I_N in parallel with a single resistance R_N ".

PROCEDURE:-

Step 1:

1. Make the connections as shown in the circuit diagram by using MATLAB Simulink.
2. Measure the response 'I' in the load resistor by considering all the sources in the network.

Step 2: Finding Norton's Resistance(R_N)

1. Open the load terminals and replace all the sources with their internal impedances.
2. Measure the impedance across the open circuited terminal which is known as Norton's Resistance.

Step 3: Finding Norton's Current(I_N)

1. Short the load terminals and measure the current through the short circuited terminals.
2. Measured current is known as Norton's Current.

Step 4: Norton's Equivalent Circuit





1. R_N and I_N are connected in parallel to the load.
2. Measure the current through the load resistor $I_L = \frac{I_N \times R_N}{R_N + R_L}$

Current measured from Norton's Equivalent Circuit should be same as current obtained from the actual circuit.

$$I = I_L.$$

Hence Norton's Theorem is Verified.

NORTON'S THEOREM



Norton's Current = 0.00745A

Norton's Resistance = 680 Ohms

Current through Load Resistor (R_L) 900 Ohms = 2.152A

With all the sources in the network Current through Load Resistor 900 Ohms = 2.152A

CONCLUSION:-

From this experiments Norton's Theorem is Verified.


EXPERIMENT NO. 8


AIM OF THE EXPERIMENT:- To simulate Single phase half wave uncontrolled rectifier with resistive load in simulink.

SOFTWARE USED:- : Matlab & Simulink

THEORY:- Rectification is a process of conversion of alternating input voltage to direct output voltage. A rectifier converts ac power to dc power. In a single phase half wave rectifier, for one cycle of supply voltage, there is one half cycle of output or load voltage. The circuit diagram is shown in the figure. During the positive half cycle, diode is forward biased, therefore it conducts from $\omega t=0^{\circ}$ to $\omega t=\pi$. During positive half cycle, output voltage V_o =source voltage V_s and load current $i_o=V_o/R$. At $\omega t=\pi$, $V_o=0$ and for R load, i_o is also zero. As soon as V_s tends to become negative after $\omega t=\pi$, diode D is reverse biased, it is therefore turned off and goes into blocking state. Output voltage as well as output current, are zero from $\omega t=\pi$ to $\omega t=2\pi$. After $\omega t=2\pi$, diode is again forward biased and conduction begins.

CIRCUIT DIAGRAM:-





CONCLUSION:- From the above experiments we able to draw the single phase half wave uncontrolled rectifier by using simulink.

EXPERIMENT NO. 9


AIM OF THE EXPERIMENT:- To simulate Single phase Full bridge uncontrolled rectifier with resistive load in simulink.


SOFTWARE USED:- : Matlab & simulink

THEORY:-

The circuit consist of four diodes D_1, D_2, D_3, D_4 and a voltage source (V) and a load R. During positive half cycle of the input voltage ,the diodes D_1 & D_3 are forward biased and current flow through $V^+ - D_1 - R - D_3 - V^-$. During negative half cycle D_2 & D_4 are forward biased and current flow through $V^+ - D_2 - R - D_4 - V^-$,the diodes D_1 & D_3 are reversed biased. The wave form show the output voltage ,output current & voltage across diodes.

CIRCUIT DIAGRAM:-





CONCLUSION:- From the above experiments we able to draw the single phase full bridge controlled rectifier by using simulink.

EXPERIMENT NO. 10


AIM OF THE EXPERIMENT:-To simulate Single phase Full bridge controlled rectifier with resistive load in simulink.


SOFTWARE USED:- : Matlab & simulink

THEORY:-

The circuit consist of four thyristor T1,T2,T3,T4 and a voltage source and a load R. During positive half cycle of the input voltage ,the thyristor T1 &T2 are forward biased and T3 & T4 are reverse biased . It does not conduct until a gate signal is applied to it and current flow through the path $v^+ - T1 - R - T2 - V^-$. During negative half cycle T3 & T4 is forward biased and the thyristor T1 &T2 are reversed biased. The current flow through the path $v^+ - T3 - R - T4 - V^-$. The wave form show the output voltage ,output current & voltage across thyristor.

CIRCUIT DIAGRAM:-






CONCLUSION:- From the above experiments we able to draw the single phase full bridge controlled rectifier by using simulink.

EXPERIMENT NO. 11

AIM OF THE EXPERIMENT:- To study the simulink model of step down chopper.


SOFTWARE USED:- : Matlab & simulink


THEORY:-



- A chopper that produces an output voltage lesser than source voltage is called step-down chopper.
- In general, DC chopper consists of power semiconductor devices like SCR, BJT, G.T.O, Power MOSFET etc. which work as a switch.
- The average output voltage across the load is control by varying the ON & OFF period of switch.
- During the period of T_{ON} chopper is ON & supply terminal are connected to the load. During the interval when chopper is OFF the load current flow through the free wheeling diode.

CIRCUIT DIAGRAM:-





CONCLUSION:- From the above experiments we able to draw bridge step down chopper by using simulink